

Little Rosie Inverter/Charger

The new Little Rosie Inverter/Charger is an exciting addition to the family of MidNite Solar Inverters!

PRODUCT FEATURES

- True sinewave inverter with charger
- 60-amp charger
- Aux input/outputs
- Listings: UL458 and CSA
- Powder-coated sheet metal enclosure
- Auto Gen Start (2-wire generators)
- Remote battery temperature sensor
- Quiet forced air cooling over heat-sink fins and transformer compartment
- Canbus communications
- Light-weight: 15 lbs.
- Built in Arlington, WA USA
- 5 year warranty



PRODUCT SPECIFICATIONS

AC Output Voltage (accuracy)	120VAC ($\pm 2\%$)
AC Input frequency range	48 to 72 Hz
Output Power (continuous @40°C)	3600W
Input Battery Voltage Range	40 to 63 VDC
Power Factor Corrected Charging	Yes
Grid/Generator Support	Yes
5 Second Surge	>5400W
Battery charge profiles	Lithium/Custom
Internal Transfer Relay Rating	50 AAC
AC input voltage limits	82 to 140 VAC

Made in the USA



www.midnitesolar.com
19115 62nd Ave NE
Arlington, WA